Arlington

Black Button™ Non-Metallic Push-In Connectors



NM94



NM942



NM95



NM96

The Black Button is not only the lowest cost NM connector on the market, but offers the fastest method of installing single or multiple cables.

For multiple cable installations:

- Two cables may be inserted together or individually
- A second cable may be added without removing the first

Plus, the NM94 meets cULus requirements for single or multiple cables.

For NM cable.


FEATURES AND BENEFITS


- Listed for both 1 or 2 cables
- Installs easily...snaps into KO using light finger pressure
- Cables insert without a struggle for a smooth installation
- Holds wires securely-meets and exceeds UL pullout tests
- Simple to remove with a twist of a screwdriver
- Arlington's Black Button™ is the lowest cost NM cable connector available today

CATALOG NUMBER	UPC/DCI/NAED MFG #018997	TRADE SIZE	KO SIZE	UNIT PKG	STD PKG	DIM A	DIM B	DIM C
NM94	05488	3/8	1/2	250	1000	1.010	.450	.096
NM940	72156	3/8	1/2	100	1000	1.010	.450	.096
NM942*	04281	3/8	1/2	250	1000	.996	.540	1.000
NM95	10956	3/4	3/4	50	500	1.293	.597	.096
NM96	72158	1	1	25	250	1.648	.683	.156

*NM942 features a divider to separate cables; cULus listed. Refer to pages C-13 and C-14 for complete cable ranges.

*PATENT PENDING. PATENTED.





INSTALLATION INSTRUCTIONS

- 1. Disconnect electrical power. Insert connector into knockout.
- **2.** Push non-metallic sheathed cable into the connector to desired length.





Q

REMOVAL

If necessary, the NM94 series may be removed with a screwdriver.

- **1.** Slip screwdriver under NM connector and twist.
- 2. NM94 pops out of the knockout.





REDUCE YOUR LABOR COSTS!

- Listed for both 1 or 2 cables
- Installs easily...snaps into KO using light finger pressure
- Cables insert without a struggle for a smooth installation
- Holds wires securely-meets and exceeds UL pullout tests
- Simple to remove with a twist of a screwdriver
- Arlington's Black Button™ is the lowest cost NM cable connector available today