Wall stud

## BRC6M cable support

## Best multiple MC cable support available





Patent Pending








Insert cables.

Bend tab as shown.

Not for use on metal studs in Canada.

Intended only to be mounted so cables run vertically.



Before cable is installed.

After cable is installed.

NOTE: Use BRC6M for metal stud mounts, and BRC6M-1 for wood stud mounts.

UPC	Catalog #	Stud Size
79903843761	BRC6M	1 1/4"
79903843762	BRC6M-1	All

Cable Type	Size	Cable Capacity
Non-Metallic Cable (NM)	14/2, 14/3, 12/2, 12/3, 10/2, 10/3, 8/2 w/ground	8
	8/3, 6/2 w/ground	6
Metal Clad Cable (MC)	14/2, 14/3, 14/4, 12/2, 12/3, 12/4, 10/2 w/ground	6
	10/3, 10/4 w/ground	5
Armored Cable (AC)	14/2, 14/3, 14/4, 12/2, 12/3, 12/4, 10/2 w/ground	6
	10/3, 10/4 w/ground	5
Flexible Conduit (BX)	5/16"	6
riexible Collduit (BA)	3/8"	5

The quantity of cables shown in the chart is the maximum. Fewer cables can be supported. Diameters are based on data from a leading cable manufacturer (may vary slightly). Diameters of some NM cables refer to the widest dimension of a flat cable. N/A = Not applicable

## Eaton

1000 Eaton Boulevard Cleveland, OH 44122 United States

© 2015 Eaton All Rights Reserved Printed in USA Publication No. IL306144EN August 2015 FIS-166

B-Line Division 509 West Monroe Street Highland, IL 62249 United States Phone: 800-851-7415

www.cooperbline.com/brc6m

Eaton is a registered trademark.

All other trademarks are property of their respective owners

Follow us on social media to get the









