



Search Parameters:

[e-Catalog](#) > [Circuit Breakers](#) > Residential Circuit Breakers

Circuit Breakers, Residential Circuit Breakers

Product #: THQL2170

Short Description: THQL 2 POLE 120/240V 10K IC 70 AMP

[Print This Page](#)

[Email This Page](#)

SPECIFICATIONS

| | |
|---------------------------------|---------------------------------|
| Category | Feeder Plug-in Circuit Breakers |
| Trip Style | Non-Interchangeable |
| Frame Type | Q-Line |
| Amperage | 70A |
| System Voltage | 120 Vac , 120/240 Vac |
| Poles | 2 |
| Trip Function | LI |
| Continuous Current Rated | Standard |
| 120 Vac Interrupting Rating | 10 KAIC |
| 120/240 Vac Interrupting Rating | 10 KAIC |
| Suitable for Reverse Feed | Yes |
| Product Line | Q-Line (Plug-In) |
| UL File # | E11592 |
| Long Time | Fixed |
| Instantaneous | Fixed |
| Protective Relays | No |
| Current Metering | No |
| Special Markings | HACR |
| GSA Compliance | Yes |
| GO Schedule | 138A |
| UPC | 078316409920 |
| List Price | \$95 |



[View Larger](#)

Publications/Resources

[THQL2170](#)

Additional Resources for Feeder Plug-in Circuit Breakers

[Application and Technical](#)

[Installation and Instruction](#)

[Time Current Curves](#)

[Buy Log :1-45](#)

Q line circuit breakers are one-inch wide per pole, compact, thermal-magnetic devices designed for residential and commercial applications. The QL breakers are plug-in versions of the Q Line used for connection to load centers and lighting panels. All Q Line circuit breakers feature Quick-make / Quick-break mechanisms, common trip bars, and easy to spot trip indication to ensure safety and reliability. Q Line breakers are available in 1, 2, and 3 pole versions, can be ordered with auxiliary contact and shunt trip accessories, and can be ordered for use in HID applications.



ORLWIDE PARTNER