

FUSE TERMINAL THERMOPLASTIC SCREW TERMINAL ON BOTH ENDS 10MM SZ1.5



Model	
product brandname	ALPHA
Type of light source / as fault indicator	without
Design of the fuse link	others
Design of fuse holder	without
General technical data	
Insulation material	thermoplastic
Terminal contact spacing	10 mm
Supply voltage	
Type of voltage / for supply of the fault indicator	others
Protection class	
Combustibility class acc. to UL 94	Other
Main circuit	
Operating voltage / rated value	250 V
Operating current / rated value	6.3 A
Appearance	
Color	miscellaneous

## Product details

Product component / required / connection plate No

## Number

Number of terminal levels 1

## Connections

### Connectable conductor cross-section / stranded

• maximum 1.5 mm<sup>2</sup>

### Connectable conductor cross-section

- solid
  - minimum 1 mm<sup>2</sup>
  - maximum 1 mm<sup>2</sup>
- finely stranded
  - with core end processing / minimum 0.75 mm<sup>2</sup>
  - with core end processing / maximum 1.5 mm<sup>2</sup>

### Type of electrical connection

- 1 screw-type terminal
- 2 screw-type terminal

Position / of the terminal lateral

## Mechanical Design

Height / with lowest-profile installation 42 mm

Length 57 mm

Mounting type DIN rail 35 mm

Material / of the insulating body Thermoplast

### General Product Approval

### Declaration of Conformity

### Test Certificates

### Shipping Approval



[sonstig](#)



### Shipping Approval

other



[Umweltbestätigung](#)

## Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/lowvoltage/catalogs>

**Industry Mall (Online ordering system)**

<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=8WA1011-1SF12>

**Service&Support (Manuals, Certificates, Characteristics, FAQs,...)**

<http://support.automation.siemens.com/WW/view/en/8WA1011-1SF12/all>

**Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)**

[http://www.automation.siemens.com/bilddb/cax\\_en.aspx?mlfb=8WA1011-1SF12](http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=8WA1011-1SF12)

**CAX-Online-Generator**

<http://www.siemens.com/cax>

**Tender specifications**

<http://www.siemens.com/specifications>